

Speech Processing through Shadow based Adaptive Filter

M. Koteswara Rao¹ I. Santhi Prabha²

1. Associate professor Department of Electronics and Communications, Srivasavi engineering college, pedatadepalli, tadepalligudem, AP, India
2. Director empowerment of women and grievances and Professor of ECE Department, Jawaharlal Nehru Technological University Kakinada (JNTUK), Kakinada, AP, India
maram_koti@yahoo.co.in, santiprabha@yahoo.com

Abstract

This paper presents a new approach to introducing adaptive Filter with LMS Algorithm based on Shadow concept. Which is useful for the cancellation of the noise component overlap with Speech signal in the same frequency range, but fixed LMS algorithm produces minimum convergence rate and fixed mean square error. In this design implements an adaptive FIR filter, based on Shadow concept, which produces minimum mean square error compare to fixed LMS, here spectral characteristics of window is improved by shadow concept, finally obtains denoised Speech signal at output, and also propose to calculate SNR and MSE values of Adaptive Filter with LMS algorithm with and without Shadow concept.

Key Words: Windows, LMS algorithm, Shadow concept

1. Adaptive Filters

Rapid Advances in the VLSI technology and digital communications/digital signal processing has brought more attention to the adaptive least squares (LS) methods [1]. Many digital signal Processing applications requires linear filters and adaptive techniques in signal processing and analysis [2]. The reference and error channels of active noise control (ANC) systems may be saturated in real-world applications if the noise level exceeds the dynamic range of the electronic devices. This nonlinear saturation degrades the performance of ANC systems that use linear adaptive filters with the filtered-least-mean-square (FLMS) algorithm [3]. Adaptive filters have been

included in the syllabus of undergraduate digital signal processing (DSP) courses[4]. The LMS algorithm has been extensively used in many applications as a consequence of its simplicity and robustness[5]. LMS based adaptive filters used in all sparse systems for noise Cancellation [6]. Adaptive algorithms are applicable to system identification and modeling, noise and interference cancelling, equalization, signal detection and prediction.[7] LMS Algorithm is widely used in a variety of applications, ranging from speech enhancement and biomedical signal processing to active control of sound and vibration[8]. Adaptive Filters are widely used in numerous industrial applications- Acoustics, communications, automatic control and seismology[9]. Information processing in variable and noisy environments is usually accomplished by means of adaptive filters [10]. Adaptive filtering is frequently employed in communications, control, and many other applications in which the statistical characteristics of the signals to be filtered are either unknown *a priori* or, in some cases, slowly time varying[11]. Adaptive filters provide performance excellence due to their inherent pole-zero structure as compared with adaptive finite impulse response (FIR) filters that have an all-zero form, in active noise control Application[12]. RLS Filters[13]. Adaptive Filters are highly stable and effectively attenuate and often cancel disturbances[14]. An Adaptive filters are successfully used in bio-medical processing systems like Denoising of ECG Waveforms[15] Adaptive filters play an important role in modern Digital signal processing products in area such as telephone echo cancellations, noise cancellation, equalization of communications channels, biomedical signal enhancement, active noise control, and adaptive control systems[16] and many Authors are worked out on FIR Filters using different Transform techniques[17] to [20]

2.Shadow Mechanism

Shadow Mechanism is successfully used in improving the spectral characteristics of windows[21] Shadow based filters are used in cardiac signal processing for elimination of noises[22].

3.Design of Adaptive Filter with fixed LMS Algorithm.

The Figure:1 shows the block diagram of Adaptive filter with Fixed LMS Algorithm. Which processes the noised speech signal through it. Where

$s(n)$ =clean speech signal

$v(n)$ =noise signal

h =Low pass FIR Filter

$v1(n)=h*v(n)$

$d(n)$ =noised speech signal, $[s(n)+v1(n)]$

$y(n)$ =Filtered Noise signal

$e(n) = d(n)-y(n)$, [Original speech signal]

the adjustable weights are typically determined by the LMS Algorithm, the weight update equation is

$w(n+1)=w(n)+\mu*e(n)*v1(n)$

$$y(n) = w(n) + e(n) * v1(n)$$

Steps to design adaptive Filter with Fixed LMS

1. Create or record actual speech signal.
2. Create or record a noise signal.
3. Correlate noise by passing through a low pass filter.
4. Merge Noise signal with actual Noise signal.
5. Pass this merged signal to Adaptive filter using Fixed LMS Algorithm.
6. Calculate error $e(n)$
7. Update weight equation $w(n)$
8. Repeat step 7 and calculate adaptive output $y(n)$ until error is minimized.
9. Calculate input SNR and output SNR

4.Design of Adaptive Filter with fixed LMS Algorithm based on Shadow concept.

The Figure:2 shows the block diagram of Adaptive filter with Fixed LMS Algorithm with Shadow concept..In shadow filter mechanism the Low pass filter output is feedback either positively or negatively by a shadow filter of same type or different type.Here we used the shadow mechanism to find best combination for different values of ' β '. Hence we can derive expression of the transfer function for the shadow mechanism with positive feedback connection is,

$$\bar{h}(n) = \frac{w_{pass Filter}^{Lo}}{1 - (\beta * Low\ pass\ Filter)}$$

$$\bar{h}(n) = \frac{h}{1 - (\beta * h)}, 0 \leq \beta \leq 1$$

$$v1(n) = v(n) * \bar{h}(n)$$




Fig1:Block diagram of Fixed LMS Adaptive Filter




Fig2:Block diagram of Shadow based LMS Adaptive Filter

5.Results and Implementations

The results shows responses of the Adaptive filter with LMS Algorithm, and we applied a noise signal to Speech and compares the signal to noise ratio of Noised signal before and after the filtering for kaiser window, which is shown in Fig3.




Fig3:Denoised speech with kaiser window

When the Noised speech is filtered with Adaptive Filter with Fixed LMS algorithm the whole noise was removed, producing a near clean signal of Fig:4 to Fig:6 with different ' β ' values of shadow FIR Filter for Kaiser window. SNR, Steady state error are computed for adaptive filter based on without shadow and with shadow concept are shown in Table-1, Table-2 Respectively.




Fig4: Denoised speech for $\beta=0.1;0.2;0.3$




Fig5: Denoised speech for $\beta=0.4;0.5;0.6$




Fig6:Denoisedspeech for $\beta=0.7;0.8;0.9$

Table1:Comparison of SNR before and after filtering of speech signal and MSE

S.NO	WINDOW	SNR before Filtering in dB	SNR after Filtering in dB	MSE (Mean Square Error)
1	Kaiser	0.0020	0.0549	1.5176e-012

Table2:Comparison of SNR and MSE for Kaiser window and shadow factors

S.NO	WINDOW	β	SNR after Filtering in dB	MSE (Mean Square Error)
1	Kaiser	0.1	0.0582	1.2204e-012
2		0.2	0.0614	1.0022e-012
3		0.3	0.0643	8.3850e-013
4		0.4	0.0671	7.1330e-013
5		0.5	0.0697	6.1598e-013
6		0.6	0.0720	5.3923e-013
7		0.7	0.0740	4.7795e-013
8		0.8	0.0756	4.2850e-013
9		0.9	0.0769	3.8824e-013
10		1.0	0.0777	3.5522e-013

6. Conclusion

The Implementation of Adaptive-FIR Filter using shadow concept for Kaiser window was performed. we applied a noised speech signal to Adaptive filter and obtained denoised wave form at output which is shown in Fig-3. Later We shown responses of shadow based Adaptive filter from Fig:4 to Fig:6 for different shadow factors. We compared SNR, mean squareerror(MSE) at input and Output which are shown from Table-1., table-2 Respectively. From the above discussions it is concluded that shadow based adaptive filter produces better responses in terms of SNR and MSE compared to Fixed Adaptive filter.

7. References:

- [1] Zhipei Chi, *Student Member, IEEE*, Jun Ma, *Member, IEEE*, and Keshab K. Parhi, *Fellow, IEEE*, "Hybrid Annihilation Transformation (HAT) for Pipelining QRD-Based Least-Square Adaptive Filters", *IEEE transactions on circuits and systems—ii: analog and digital signal processing*, vol. 48, no. 7, July 2001 661
- [2] Daniel J. Allred, *Student Member, IEEE*, Heejong Yoo, *Student Member, IEEE*, Venkatesh Krishnan, *Student Member, IEEE*, Walter Huang, *Student Member, IEEE*, and David V. Anderson, *Senior Member, IEEE*, "LMS Adaptive Filters Using Distributed Arithmetic for High Throughput", *IEEE transactions on circuits and systems—i: regular papers*, vol. 52, no. 7, July 2005 1327
- [3] Sen M. Kuo, *Senior Member, IEEE*, and Hsien-Tsai Wu, *Member, IEEE*, "Nonlinear Adaptive Bilinear Filters for Active Noise Control Systems", *IEEE transactions on circuits and systems—i: regular papers*, vol. 52, no. 3, March 2005 617
- [4] Emilio Soria, Javier Calpe, *Member, IEEE*, Jonathon Chambers, *Senior Member, IEEE*, Marcelino Martínez, Gustavo Camps, *Member, IEEE*, and José David Martín Guerrero, "A Novel Approach to Introducing Adaptive Filters Based on the LMS Algorithm and Its Variants", *IEEE transactions on education*, vol. 47, no. 1, February 2004 127
- [5] Yonggang Zhang and Jonathon A. Chambers, *Senior Member, IEEE*, "Convex Combination of Adaptive Filters for a Variable Tap-Length LMS Algorithm", *IEEE signal processing letters*, vol. 13, no. 10, October 2006
- [6] Bijit Kumar Das and Mrityunjay Chakraborty, *Senior Member, IEEE*, "Sparse Adaptive Filtering by an Adaptive Convex Combination of the LMS and the z-lms algorithms", *IEEE transactions on circuits and systems—i: regular papers*, vol. 61, no. 5, May 2014 1499
- [7] Márcio H. Costa, José Carlos M. Bermudez, *Member, IEEE*, and Neil J. Bershad, *Fellow, IEEE*, "Stochastic Analysis of the LMS Algorithm with a Saturation Nonlinearity Following the Adaptive Filter Output", *IEEE transactions on signal processing*, vol. 49, no. 7, July 2001

- [8] Boaz Rafaely, *Member, IEEE*, and Stephen J. Elliott, *Senior Member, IEEE*, "A Computationally Efficient Frequency-Domain LMS Algorithm with Constraints on the Adaptive Filter", *IEEE Transactions on Signal Processing*, vol. 48, no. 6, June 2000
- [9] Shin'ichi Koike, *Member, IEEE*, "Analysis of Adaptive Filters Using Normalized Signed Regressor LMS Algorithm", *IEEE Transactions on Signal Processing*, vol. 47, no. 10, October 1999
- [10] Jerónimo Arenas-García, *Member, IEEE*, Vanessa Gómez-Verdejo, and Aníbal R. Figueiras-Vidal, *Senior Member, IEEE*, "New Algorithms for Improved Adaptive Convex Combination of LMS Transversal Filters", *New Algorithms for Improved Adaptive Convex Combination of LMS Transversal Filters*, *IEEE Transactions on Instrumentation and Measurement*, vol. 54, no. 6, December 2005 2239
- [11] Y. Zhou, S. C. Chan, and K. L. Ho, "A New Block-Exact Fast LMS/Newton Adaptive Filtering Algorithm", *IEEE TRANSACTIONS ON SIGNAL PROCESSING*, VOL. 54, NO. 1, JANUARY 2006
- [12] ibtissam constantin, regis lengelle-"performance analysis of kernel adaptive filters based on lms algorithm"-*procedia computer science* 20(2013) 39-45, *sciencedirect*.
- [13] michael a. vaudrey, william t. baumann, william r. saunders-"stability and operating constraints of adaptive lms-based feedback control"-*automatica*-*sciencedirect*
- [14] wang an-dong, liulan, weiqin-"an adaptive morphologic filter applied to ecg de-noising and extraction of r peak at real-time" 2012 *aasri conference on computational intelligence and bioinformatics*, *elsevier*
- [15] kaibohu*, yaxuanliu-"adaptive noise cancellation method for fiber optic gyroscope"- 2012 *international workshop on information and electronics engineering* (iwiee), *elsevier*
- [16] p.v.muralidhar, v. l. n.sastri d, s.k.nayak, "interpretation of dirichlet, bartlett, hanning and hamming windows using fractional fourier transform", *international journal of scientific & engineering research*, vol. 4, issue 6, June-2013.
- [17] muralidhar, p. v. DVLN sastry, and s.k.Nayak. "spectral analysis of shadow window-fir filters." *int. conf. on advances in communication, network, and computing*. 2013.]
- [18] p.v.muralidhar, a.s.rao, s.k.nayak, "spectral interpretation of sinusoidal wave using fractional fourier transform based fir window functions"-*international review of computers and software* 4.6(2009).
- [19] Muralidhar.p.v., a.s.srinivasarao, dr.s.k.nayak" fractional fourier transform based fir window functions"-*proceedings of IInd international conference rspi-2010 sponsored by IEEE (Hyderabad section)*.
- [20] Muralidhar P.V, D.Natraj, V.LokeshRaju and S.K.nayak "Implementation of different FIR high pass filters using Fractional Kaiser window" 2010 *IEEE International Conference*, vol:2, pp 651

- [21] P. V. Muralidhar¹, D.V.L.N. Sastry² and S. K. Naik, '' Spectral Analysis of Shadow Window-FIR Filters', *Proc. of Int. Conf. on Advances in Communication, Network, and Computing 2013*'
- [22] N.MohanaRao, A.S.SrinivasaRao, P.V.Muralidhar, Venkata L N Sastry.D, '' **Noise Removal in Cardiac Signal by Shadow Digital Filters**'', International Journal of Engineering Research & Technology (IJERT)Vol. 2 Issue 10, October – 2013, issn:2278-0181

8.Author's profile:

First Author: M. Koteswara Rao obtained M. Tech from JNTUK, Kakinada, pursuing PhD from JNTUK Kakinada. He is having an experience more than 15 years and also having more number of both national and international journals, conferences. His area of interest is speech signal processing, presently working as associate professor in Sri Vasavi engineering college, Pedatadepalli, Tadepalligudem, A.P.



Second Author: Dr. I. Santi Prabha is working as Professor in ECE Department and Director of Empowerment of women & Grievances in Jawaharlal Nehru Technological University, Kakinada. She did her B.Tech & M.Tech with specialization in Instrumentation and Control Systems from JNTU College of engineering, Kakinada. She was awarded with Ph.D. in Speech signal processing by Jawaharlal Nehru Technological University in 2005. She has 26 years experience of teaching to UG and PG classes and has received good response from the students. She has also 15 years of Research experience. She has produced two Ph.D. and guiding 7 Ph.D scholars. She has guided more than 50 M.Tech. projects. She is a member of I.S.T.E. and fellow member in I.E.T.E. & I.E. She has published 35 technical papers in national and International journals and conferences. She worked as Head of ECE Department and Deputy Warden for Lady's hostel, JNTUK, Kakinada.